wireless TV link

SBC VL1400

- *Links Pay-TV, VCR, DVD and Satellite receiver to your second TV*
- *No more cable laying or hole drilling!*
- *4 video source inputs*
- *Six-in-one universal remote control*
- *Wireless RF system*
- *Plug & Play installation for all A/V brands*
- *No need to swap SCART cables*

DVD

VCR

Satellite

Pay TV

Set-top box

Camcorder

Let's make things better.

PHILIPS

Wireless TV Link

SBC VL1400

General product information

• Power supply	12V DC via 220-240 VAC/ 50 Hz adapter
• Power consumption	7 Watts
• Operating / storage temperature	5 to 45°C / -25 to 55°C
• Plug and Play system	via SCART connectors
• Number of A/V source inputs	4
• Audio L/R out transmitter	yes (RCA)
• SCART switchbox (RGB enabled)	yes (can be overruled manually)
• Universal Remote Control	included: 6 in 1 (LINK, TV, VCR, DVD, SAT, CBL)

Wireless Audio/Video performance

• Supported video standards	CVBS: PAL/NTSC/SECAM
• Video output	1Vpp into 75ohm
• Signal noise	47dB ± 6dB
• Audio format	Stereo (L + R)
• Freq. Range	70 Hz – 20kHz (± 3dB)
• Signal Noise	58dB ± 7dB
• Crosstalk (1kHz)	45dB, min.
• Distortion (1kHz)	2%, max.

RF A/V system information

• Typical range	up to 100 m in open air, up to 30 m indoors
• Carrier frequency	2.4 GHz / FM mod.
• Transmission power	<10 mW
• Multiple RF channels	4* to allow interference-free operation
• Antenna	built-in

** May vary per country according to local regulations*

RF Control system information

• IR carrier freq. Range	32-57kHz (universal remote control extender)
• RF carrier frequency	433.92 MHz / AM mod.
• RF transmission power	<10 mW
• Antenna	external

Features

• Remote switching	yes
• Automatic power on/off transmitter	yes
• Wireless Link RC operatable	yes
• Easylink compatible	yes
• Auto format switching	yes (on transmitter)
• Link A/V input sources to CVR/DVD+RW	yes

Transmitter unit

• Dimensions (w x h x d)	270 x 61 x 150 mm
• Power standby/on switch	on the front
• View source on transmitter switch	on the front
• Indication selected input on transmitter	7 segment LED display
• Link input source to input 4 (VCR / DVD+RW)	on the front
• Indication link source	LEDs
• SCART Input	3 SCART (RBG / CVBS + audio L/R)
• SCART In/Output	In: as SCART input, Out:CVBS + audio L/R
• SCART Output	1 SCART (RBG / CVBS + audio L/R)
• Audio out	RCA L/R

Receiver unit

• Dimensions (w x h x d)	61 x 146 x 150 mm
• View source on receiver switches (+/-)	on the front
• Power standby/on switch	on the front
• SCART output	1 SCART CVBS + audio L/R
• Capture range of IR receiver	up to 7 meters max.

Packaging contents

- 1 transmitter unit
- 1 receiver unit
- 1 Universal Remote Control
- 2 SCART cables
- 2 power supply adapters
- 1 RC extender cord (4 IR LEDs)
- 1 Instructions for use booklet

Links Pay-TV, VCR, DVD and Satellite receiver to your second TV!
The Philips SBC VL1400 Wireless TV Link lets you watch, control and enjoy A/V content on both your main TV and a second TV located anywhere else in your house. There's no need to buy or rent duplicate A/V equipment, and two people can watch and enjoy two different things.

No more cable laying or hole drilling!
Because the SBC VL1400 uses a wireless RF link, there's no drilling holes or running cables upstairs to be able to watch your video devices on other locations in your home.

4 video source inputs
The Wireless TV Link has four separate inputs, each with its own SCART connector, to allow you to connect up to four A/V source devices at the same time. It works as a switchbox for both your main and second TV.

Six-in-one universal remote control
There's no need to walk to the receiver either, because a six-in-one universal remote control is supplied to make it possible to operate the transmitter and receiver, and up to five video sources from the second TV. And it works with every brand of A/V equipment too. When you switch on the receiver and select an input source, the transmitter is automatically switched on

Wireless RF system
By transmitting crystal clear pictures and stereo sound through walls and ceilings to your second TV, it extends your possibilities for viewing movies, sports events, live performances and an incredibly wide range of TV channels anywhere in your home. The range is up to 30 meters indoors. A multiple-position slide-switch allows different transmission frequencies to be selected to avoid interference from other RF devices.

Plug & Play installation for all A/V brands
Install any brand of TV, VCR, DVD, satellite receiver, Pay-TV decoder or any other device with a SCART connector in minutes.

No need to swap SCART cables
The SCART switchbox functionality means that all your video devices are available for both your main and secondary TV at all times. This makes it easy to switch between your DVD player, satellite receiver, VCR and set-top box without reconfiguring your entire home cinema set-up.

Helpdesk available
Should you have any questions, comments or recommendations about the Wireless TV Link, please call our helpdesk.

Helpdesk available

Philips Accessories & Recordable Media

Data subject to change without notice
©2002 Royal Philips Electronics
All rights reserved

http://www.philips.com

Let's make things better.

PHILIPS